

# Enphase IQ 6 and IQ 6+ Microinverters

The high-powered smart grid-ready **Enphase IQ 6 Micro™** and **Enphase IQ 6+ Micro™** dramatically simplify the installation process while achieving the highest efficiency for module-level power electronics.

Part of the Enphase IQ System, the IQ 6 and IQ 6+ Micro integrate seamlessly with the Enphase IQ Envoy™, Enphase Q Aggregator™, Enphase IQ Battery™, and the Enphase Enlighten™ monitoring and analysis software.

The IQ 6 and IQ 6+ Micro extend the reliability standards set forth by previous generations and undergo over a million hours of power-on testing, enabling Enphase to provide an industry-leading warranty of up to 25 years.



## Easy to Install

- Lightweight and simple
- Faster installation with improved two-wire cabling
- Built-in rapid shutdown compliant (NEC 2014 & 2017)

## Productive and Reliable

- Optimized for high powered 60-cell and 72-cell\* modules
- More than a million hours of testing
- Class II double-insulated enclosure
- UL listed

## Smart Grid Ready

- Complies with fixed power factor, voltage and frequency ride-through requirements
- Remotely updates to respond to changing grid requirements
- Configurable for varying grid profiles
- Meets CA Rule 21 (UL 1741-SA)

\* The IQ 6+ Micro is required to support 72-cell modules



# Enphase IQ 6 and IQ 6+ Microinverters

<b>INPUT DATA (DC)</b>	<b>IQ6-60-2-US</b>		<b>IQ6PLUS-72-2-US</b>	
Commonly used module pairings <sup>1</sup>	195 W - 330 W +		235 W - 400 W +	
Module compatibility	60-cell PV modules only		60-cell and 72-cell PV modules	
Maximum input DC voltage	48 V		62 V	
Peak power tracking voltage	27 V - 37 V		27 V - 45 V	
Operating range	16 V - 48 V		16 V - 62 V	
Min/Max start voltage	22 V / 48 V		22 V / 62 V	
Max DC short circuit current (module I <sub>sc</sub> )	15 A		15 A	
Overvoltage class DC port	II		II	
DC port backfeed under single fault	0 A		0 A	
PV array configuration	1 x 1 ungrounded array; No additional DC side protection required; AC side protection requires max 20A per branch circuit			
<b>OUTPUT DATA (AC)</b>	<b>IQ 6 Microinverter</b>		<b>IQ 6+ Microinverter</b>	
Peak output power	240 VA		290 VA	
Maximum continuous output power	230 VA		280 VA	
Nominal (L-L) voltage/range <sup>2</sup>	240 V / 211-264 V	208 V / 183-229 V	240 V / 211-264 V	208 V / 183-229 V
Maximum continuous output current	0.96 A	1.11 A	1.17 A	1.35 A
Nominal frequency	60 Hz		60 Hz	
Extended frequency range	47 - 68 Hz		47 - 68 Hz	
Power factor at rated power	1.0		1.0	
Maximum units per 20 A (L-L) branch circuit	16 (240 VAC)		13 (240 VAC)	
	14 (208 VAC)		11 (208 VAC)	
Overvoltage class AC port	III		III	
AC port backfeed under single fault	0 A		0 A	
Power factor (adjustable)	0.7 leading ... 0.7 lagging		0.7 leading ... 0.7 lagging	
<b>EFFICIENCY</b>	<b>@240 V</b>	<b>@208 V</b>	<b>@240 V</b>	<b>@208 V</b>
CEC weighted efficiency	97.0 %	97.0 %	97.0 %	97.0 %
<b>MECHANICAL DATA</b>				
Ambient temperature range	-40°C to +65°C			
Relative humidity range	4% to 100% (condensing)			
Connector type	MC4 locking type			
Dimensions (WxHxD)	219 mm x 191 mm x 37.9 mm (without bracket)			
Weight	1.29 kg (2.84 lbs)			
Cooling	Natural convection - No fans			
Approved for wet locations	Yes			
Pollution degree	PD3			
Enclosure	Class II double-insulated			
Environmental category / UV exposure rating	NEMA Type 6 / outdoor			
<b>FEATURES</b>				
Communication	Power line			
Monitoring	Enlighten Manager and MyEnlighten monitoring options Compatible with Enphase IQ Envoy			
Disconnecting means	The AC and DC connectors have been evaluated and approved by UL for use as the load-break disconnect required by NEC 690.			
Compliance	CA Rule 21 (UL 1741-SA) UL 62109-1, UL1741/IEEE1547, FCC Part 15 Class B, ICES-0003 Class B, CAN/CSA-C22.2 NO. 107.1-01 This product is UL Listed as PV Rapid Shut Down Equipment and conforms with NEC-2014 and NEC-2017 section 690.12 and C22.1-2015 Rule 64-218 Rapid Shutdown of PV Systems, for AC and DC conductors, when installed according manufacturer's instructions.			

1. No enforced DC/AC ratio. See the compatibility calculator at <https://enphase.com/en-us/support/module-compatibility>.
2. Nominal voltage range can be extended beyond nominal if required by the utility.

To learn more about Enphase offerings, visit [enphase.com](https://enphase.com)